

# ATTESTATION OF CONFORMITY

Issued to: Afore New Energy Technology (Shanghai) Co., Ltd.  
Build No.7, 333 Wanfang Road, Minhang District, Shanghai, China

For the product: On-Grid PV Inverter

Trade name:



Type/Model: BNT003KTL, BNT004KTL, BNT005KTL, BNT006KTL, BNT008KTL  
BNT010KTL

Ratings: See Annex

Manufactured by: Afore New Energy Technology (Shanghai) Co., Ltd.  
Build No.7, 333 Wanfang Road, Minhang District, Shanghai, China

Requirements: Engineering Recommendation G98 Issue 1 – Amendment 7: 2022

This Attestation is granted on account of an examination by DEKRA, the results of which are laid down in a confidential file no. 6136782.52

The examination has been carried out on one single specimen or several specimens of the product, submitted by the manufacturer. The Attestation does not include an assessment of the manufacturer's production. Conformity of his production with the specimen tested by DEKRA is not the responsibility of DEKRA.

Arnhem, 8 June 2023

Number: 6136782.03AOC

DEKRA Testing and Certification (Shanghai) Ltd.

Kreny Lin  
Certification Manager

A handwritten signature in black ink, appearing to read "Kreny Lin".

© Integral publication of this attestation and adjoining reports is allowed

Page 1 of 21

DEKRA Testing and Certification (Shanghai) Ltd.  
3F #250 Jiangchangsan Road Shibei Hi-Tech Park, 200436 Jing'an District, Shanghai, China  
T +86 21 6056 7666 F +86 21 6056 7555 www.dekra-product-safety.com

## Annex to 6136782.03AOC

Ratings of the test product:

Operating temperature range: - 25°C to + 60°C

Protective class: I

Ingress protection rating: IP65

Power factor range (adjustable): 0.8 leading...0.8 lagging

BNT003KTL:

PV input: Max. 1100 Vdc, MPPT voltage range: 150-1000 Vdc, max 15\*2 A, Isc PV: 25\*2 A

AC Output: 3P+N+PE/ 3P+PE, 230/ 400 Vac, 50/ 60 Hz, Nominal 3000 VA, rated 4.4 A, max 5.3 A

BNT004KTL:

PV input: Max. 1100 Vdc, MPPT voltage range: 150-1000 Vdc, max 15\*2 A, Isc PV: 25\*2 A

AC Output: 3P+N+PE/ 3P+PE, 230/ 400 Vac, 50/ 60 Hz, Nominal 4000 VA, rated 5.8 A, max 7.0 A

BNT005KTL:

PV input: Max. 1100 Vdc, MPPT voltage range: 150-1000 Vdc, max 15\*2 A, Isc PV: 25\*2 A

AC Output: 3P+N+PE/ 3P+PE, 230/ 400 Vac, 50/ 60 Hz, Nominal 5000 VA, rated 7.3 A, max 8.5 A

BNT006KTL:

PV input: Max. 1100 Vdc, MPPT voltage range: 150-1000 Vdc, max 15\*2 A, Isc PV: 25\*2 A

AC Output: 3P+N+PE/ 3P+PE, 230/ 400 Vac, 50/ 60 Hz, Nominal 6000 VA, rated 8.7 A, max 10.5 A

BNT008KTL:

PV input: Max. 1100 Vdc, MPPT voltage range: 150-1000 Vdc, max 15\*2 A, Isc PV: 25\*2 A

AC Output: 3P+N+PE/ 3P+PE, 230/ 400 Vac, 50/ 60 Hz, Nominal 8000 VA, rated 11.6 A, max 13.5 A

BNT010KTL:

PV input: Max. 1100 Vdc, MPPT voltage range: 150-1000 Vdc, max 15\*2 A, Isc PV: 25\*2 A

AC Output: 3P+N+PE/ 3P+PE, 230/ 400 Vac, 50/ 60 Hz, Nominal 10000 VA, rated 14.5 A, max 17.0 A

|  |                   |
|--|-------------------|
| <b>G98/1-7 Form C: Type Test Verification Report</b> |                   |
| <b>Extract form test report number.:</b>             | <b>6136782.52</b> |

|  |                         |                      |                       |                     |
|--|-------------------------|----------------------|-----------------------|---------------------|
| <b>1. Operating Range:</b>   |                         |                      |                       | <b>P</b>            |
| <p>This test should be carried out as specified in A.1.2.10.</p> <p>Pass or failure of the test should be indicated in the fields below (right hand side), for example with the statement "Pass", "No disconnection occurs", etc. Graphical evidence is preferred.</p> |                         |                      |                       |                     |
| Model: BNT010KTL   |                         |                      |                       |                     |
| <b>Test 1:</b>   |                         |                      |                       |                     |
| Measured Voltage (V)   | Measured Frequency (Hz) | Measured Power (W)   | Measured Power factor | Test Time (seconds) |
| 195.61   | 47.00                   | 9889.91              | 0.9994                | 20                  |
| <b>Test 2:</b>   |                         |                      |                       |                     |
| Measured Voltage (V)   | Measured Frequency (Hz) | Measured Power (W)   | Measured Power factor | Test Time (Minutes) |
| 195.62   | 47.50                   | 9886.80              | 0.9994                | 90                  |
| <b>Test 3:</b>   |                         |                      |                       |                     |
| Measured Voltage (V)   | Measured Frequency (Hz) | Measured Power (W)   | Measured Power factor | Test Time (Minutes) |
| 253.04   | 51.50                   | 10070.87             | 0.9979                | 90                  |
| <b>Test 4:</b>   |                         |                      |                       |                     |
| Measured Voltage (V)   | Measured Frequency (Hz) | Measured Power (W)   | Measured Power factor | Test Time (Minutes) |
| 253.08   | 52.00                   | 10069.46             | 0.9979                | 15                  |
| <b>Test 5:</b>   |                         |                      |                       |                     |
| Measured Voltage (V)   | Measured Frequency (Hz) | Measured Power (W)   | Measured Power factor | Test Time (Minutes) |
| 230.56   | 50.00                   | 10075.42             | 0.9989                | 90                  |
| <b>Test 6:</b>   |                         |                      |                       |                     |
| Measured Voltage (V)   | Ramp range              | Test frequency ramp  | Test Duration         | Confirm no trip     |
| 195.5  | 47.0 Hz to 52.0 Hz      | +1 Hzs <sup>-1</sup> | 5.0s                  | No trip             |
| 253.0  | 52.0 Hz to 49.0 Hz      | -1 Hzs <sup>-1</sup> | 3.0s                  | No trip             |



| <b>2. Power Quality – Harmonics:</b>   |   |                               |                                    |                               |                                  | <b>P</b>                                    |
|--|---|-------------------------------|------------------------------------|-------------------------------|----------------------------------|---|
| These tests should be carried out as specified in BS EN 61000-3-2. The chosen test should be undertaken with a fixed source of energy at two power levels a) between 45 and 55% and b) at 100% of <b>Registered Capacity</b> . The test requirements are specified in Annex A1 A.1.3.1 ( <b>Inverter</b> connected) or Annex A2 A.2.3.1 (Synchronous). |   |                               |                                    |                               |                                  |   |
| Model: BNT003KTL   |   |                               |                                    |                               |                                  |   |
| L1   |   |                               |                                    |                               |                                  |   |
| <b>Micro-generator</b> tested to BS EN 61000-3-2   |   |                               |                                    |                               |                                  |   |
| <b>Micro-generator</b> rating per phase (rpp)  |   |                               |                                    | 1                             | kW                               |   |
| For 3-phase <b>Micro-generators</b> , tick this box if harmonic measurements are identical for all three phases. If the harmonics are not identical for each phase, please replicate this section with the results for each phase.   |   |                               |                                    | three phase PV inverter       |                                  |   |
| Harmonic   | At 45-55% of <b>Registered Capacity</b> |                               | 100% of <b>Registered Capacity</b> |                               |                                  |   |
|  | Measured Value MV in Amps               | Normalised Value (NV) in Amps | Measured Value MV in Amps          | Normalised Value (NV) in Amps | Limit in BS EN 61000-3-2 in Amps | Higher limit for odd harmonics 21 and above |
| 2  | 0.018                                   | 0.132                         | 0.026                              | 0.096                         | 1.080                            |   |
| 3  | 0.070                                   | 0.514                         | 0.028                              | 0.103                         | 2.300                            |   |
| 4  | 0.011                                   | 0.077                         | 0.011                              | 0.042                         | 0.430                            |   |
| 5  | 0.140                                   | 1.027                         | 0.120                              | 0.442                         | 1.140                            |   |
| 6  | 0.008                                   | 0.060                         | 0.008                              | 0.030                         | 0.300                            |   |
| 7  | 0.064                                   | 0.474                         | 0.052                              | 0.192                         | 0.770                            |   |
| 8  | 0.010                                   | 0.074                         | 0.006                              | 0.024                         | 0.230                            |   |
| 9  | 0.028                                   | 0.202                         | 0.009                              | 0.033                         | 0.400                            |   |
| 10   | 0.010                                   | 0.074                         | 0.007                              | 0.026                         | 0.184                            |   |
| 11   | 0.149                                   | 0.275                         | 0.024                              | 0.086                         | 0.330                            |   |
| 12   | 0.013                                   | 0.093                         | 0.005                              | 0.020                         | 0.153                            |   |
| 13   | 0.057                                   | 0.140                         | 0.037                              | 0.136                         | 0.210                            |   |
| 14   | 0.005                                   | 0.039                         | 0.006                              | 0.024                         | 0.131                            |   |
| 15   | 0.019                                   | 0.144                         | 0.005                              | 0.020                         | 0.150                            |   |
| 16   | 0.006                                   | 0.047                         | 0.005                              | 0.019                         | 0.115                            |   |
| 17   | 0.020                                   | 0.048                         | 0.032                              | 0.059                         | 0.132                            |   |
| 18   | 0.007                                   | 0.048                         | 0.005                              | 0.019                         | 0.102                            |   |
| 19   | 0.006                                   | 0.043                         | 0.038                              | 0.024                         | 0.118                            |   |
| 20   | 0.005                                   | 0.035                         | 0.006                              | 0.021                         | 0.092                            |   |
| 21   | 0.011                                   | 0.081                         | 0.010                              | 0.038                         | 0.107                            | 0.160                                       |
| 22   | 0.007                                   | 0.051                         | 0.006                              | 0.021                         | 0.084                            |   |
| 23   | 0.035                                   | 0.085                         | 0.039                              | 0.024                         | 0.098                            | 0.147                                       |
| 24   | 0.006                                   | 0.043                         | 0.007                              | 0.024                         | 0.077                            |   |
| 25   | 0.040                                   | 0.060                         | 0.024                              | 0.088                         | 0.090                            | 0.135                                       |
| 26   | 0.004                                   | 0.032                         | 0.006                              | 0.021                         | 0.071                            |   |

# Annex to 6136782.03AOC

|    |       |       |       |       |       |       |
|----|-------|-------|-------|-------|-------|-------|
| 27 | 0.008 | 0.058 | 0.011 | 0.041 | 0.083 | 0.124 |
| 28 | 0.004 | 0.032 | 0.005 | 0.018 | 0.066 |       |
| 29 | 0.018 | 0.027 | 0.023 | 0.028 | 0.078 | 0.117 |
| 30 | 0.005 | 0.038 | 0.007 | 0.025 | 0.061 |       |
| 31 | 0.010 | 0.040 | 0.022 | 0.021 | 0.073 | 0.109 |
| 32 | 0.005 | 0.036 | 0.005 | 0.018 | 0.058 |       |
| 33 | 0.004 | 0.031 | 0.008 | 0.029 | 0.068 | 0.102 |
| 34 | 0.005 | 0.035 | 0.004 | 0.015 | 0.054 |       |
| 35 | 0.013 | 0.049 | 0.011 | 0.007 | 0.064 | 0.096 |
| 36 | 0.005 | 0.038 | 0.005 | 0.018 | 0.051 |       |
| 37 | 0.021 | 0.039 | 0.016 | 0.020 | 0.061 | 0.091 |
| 38 | 0.003 | 0.024 | 0.004 | 0.015 | 0.048 |       |
| 39 | 0.009 | 0.018 | 0.006 | 0.024 | 0.058 | 0.087 |
| 40 | 0.003 | 0.025 | 0.004 | 0.016 | 0.046 |       |

Note the higher limits for odd harmonics 21 and above are only allowable under certain conditions, if these higher limits are utilised please state the exemption used as detailed in part 6.2.3.4 of BS EN 61000-3-2 in the box below.

| Model: BNT003KTL   |   |                               |                                    |                               |                                  |   |
|--|---|-------------------------------|------------------------------------|-------------------------------|----------------------------------|---|
| L2   |   |                               |                                    |                               |                                  |   |
| Micro-generator tested to BS EN 61000-3-2  |   |                               |                                    |                               |                                  |   |
| Micro-generator rating per phase (rpp)   |   |                               |                                    | 1                             | kW                               |   |
| For 3-phase <b>Micro-generators</b> , tick this box if harmonic measurements are identical for all three phases. If the harmonics are not identical for each phase, please replicate this section with the results for each phase. |   |                               |                                    | three phase PV inverter       |                                  |   |
| Harmonic   | At 45-55% of <b>Registered Capacity</b> |                               | 100% of <b>Registered Capacity</b> |                               |                                  |   |
|  | Measured Value MV in Amps               | Normalised Value (NV) in Amps | Measured Value MV in Amps          | Normalised Value (NV) in Amps | Limit in BS EN 61000-3-2 in Amps | Higher limit for odd harmonics 21 and above |
| 2  | 0.018                                   | 0.132                         | 0.025                              | 0.090                         | 1.080                            |   |
| 3  | 0.079                                   | 0.581                         | 0.043                              | 0.159                         | 2.300                            |   |
| 4  | 0.010                                   | 0.078                         | 0.012                              | 0.046                         | 0.430                            |   |
| 5  | 0.152                                   | 1.120                         | 0.172                              | 0.633                         | 1.140                            |   |
| 6  | 0.010                                   | 0.071                         | 0.009                              | 0.032                         | 0.300                            |   |
| 7  | 0.081                                   | 0.598                         | 0.100                              | 0.367                         | 0.770                            |   |
| 8  | 0.008                                   | 0.060                         | 0.007                              | 0.024                         | 0.230                            |   |
| 9  | 0.035                                   | 0.262                         | 0.025                              | 0.093                         | 0.400                            |   |
| 10   | 0.010                                   | 0.069                         | 0.008                              | 0.030                         | 0.184                            |   |
| 11   | 0.151                                   | 0.139                         | 0.046                              | 0.171                         | 0.330                            |   |
| 12   | 0.009                                   | 0.063                         | 0.006                              | 0.022                         | 0.153                            |   |
| 13   | 0.082                                   | 0.077                         | 0.046                              | 0.169                         | 0.210                            |   |

# Annex to 6136782.03AOC

|    |       |       |       |       |       |       |
|----|-------|-------|-------|-------|-------|-------|
| 14 | 0.007 | 0.049 | 0.007 | 0.026 | 0.131 |       |
| 15 | 0.011 | 0.082 | 0.021 | 0.079 | 0.150 |       |
| 16 | 0.005 | 0.036 | 0.006 | 0.021 | 0.115 |       |
| 17 | 0.018 | 0.035 | 0.040 | 0.048 | 0.132 |       |
| 18 | 0.005 | 0.039 | 0.006 | 0.023 | 0.102 |       |
| 19 | 0.007 | 0.054 | 0.034 | 0.042 | 0.118 |       |
| 20 | 0.005 | 0.038 | 0.007 | 0.025 | 0.092 |       |
| 21 | 0.005 | 0.034 | 0.009 | 0.032 | 0.107 | 0.160 |
| 22 | 0.006 | 0.042 | 0.005 | 0.020 | 0.084 |       |
| 23 | 0.033 | 0.049 | 0.036 | 0.044 | 0.098 | 0.147 |
| 24 | 0.005 | 0.040 | 0.006 | 0.023 | 0.077 |       |
| 25 | 0.032 | 0.047 | 0.023 | 0.083 | 0.090 | 0.135 |
| 26 | 0.007 | 0.049 | 0.007 | 0.025 | 0.071 |       |
| 27 | 0.006 | 0.040 | 0.008 | 0.031 | 0.083 | 0.124 |
| 28 | 0.004 | 0.032 | 0.006 | 0.023 | 0.066 |       |
| 29 | 0.021 | 0.031 | 0.028 | 0.026 | 0.078 | 0.117 |
| 30 | 0.005 | 0.033 | 0.005 | 0.020 | 0.061 |       |
| 31 | 0.012 | 0.018 | 0.020 | 0.019 | 0.073 | 0.109 |
| 32 | 0.004 | 0.032 | 0.005 | 0.020 | 0.058 |       |
| 33 | 0.007 | 0.053 | 0.008 | 0.028 | 0.068 | 0.102 |
| 34 | 0.006 | 0.047 | 0.008 | 0.030 | 0.054 |       |
| 35 | 0.018 | 0.034 | 0.018 | 0.022 | 0.064 | 0.096 |
| 36 | 0.005 | 0.038 | 0.007 | 0.027 | 0.051 |       |
| 37 | 0.014 | 0.026 | 0.015 | 0.056 | 0.061 | 0.091 |
| 38 | 0.005 | 0.040 | 0.009 | 0.034 | 0.048 |       |
| 39 | 0.007 | 0.053 | 0.007 | 0.025 | 0.058 | 0.087 |
| 40 | 0.006 | 0.042 | 0.007 | 0.024 | 0.046 |       |

Note the higher limits for odd harmonics 21 and above are only allowable under certain conditions, if these higher limits are utilised please state the exemption used as detailed in part 6.2.3.4 of BS EN 61000-3-2 in the box below.

| Model: BNT003KTL   |   |                               |                                    |                               |                                  |   |
|--|---|-------------------------------|------------------------------------|-------------------------------|----------------------------------|---|
| L3   |   |                               |                                    |                               |                                  |   |
| Micro-generator tested to BS EN 61000-3-2  |   |                               |                                    |                               |                                  |   |
| Micro-generator rating per phase (rpp)   |   |                               |                                    | 1                             | kW                               |   |
| For 3-phase <b>Micro-generators</b> , tick this box if harmonic measurements are identical for all three phases. If the harmonics are not identical for each phase, please replicate this section with the results for each phase. |   |                               |                                    | three phase PV inverter       |                                  |   |
| Harmonic   | At 45-55% of <b>Registered Capacity</b> |                               | 100% of <b>Registered Capacity</b> |                               |                                  |   |
|  | Measured Value MV in Amps               | Normalised Value (NV) in Amps | Measured Value MV in Amps          | Normalised Value (NV) in Amps | Limit in BS EN 61000-3-2 in Amps | Higher limit for odd harmonics 21 and above |
| 2  | 0.016                                   | 0.121                         | 0.031                              | 0.113                         | 1.080                            |   |
| 3  | 0.035                                   | 0.258                         | 0.033                              | 0.121                         | 2.300                            |   |
| 4  | 0.011                                   | 0.078                         | 0.013                              | 0.047                         | 0.430                            |   |
| 5  | 0.082                                   | 0.595                         | 0.102                              | 0.376                         | 1.140                            |   |
| 6  | 0.009                                   | 0.066                         | 0.010                              | 0.038                         | 0.300                            |   |
| 7  | 0.042                                   | 0.310                         | 0.063                              | 0.229                         | 0.770                            |   |
| 8  | 0.009                                   | 0.067                         | 0.006                              | 0.023                         | 0.230                            |   |
| 9  | 0.018                                   | 0.130                         | 0.024                              | 0.090                         | 0.400                            |   |
| 10   | 0.009                                   | 0.066                         | 0.007                              | 0.024                         | 0.184                            |   |
| 11   | 0.130                                   | 0.121                         | 0.041                              | 0.149                         | 0.330                            |   |
| 12   | 0.009                                   | 0.064                         | 0.006                              | 0.021                         | 0.153                            |   |
| 13   | 0.084                                   | 0.105                         | 0.033                              | 0.123                         | 0.210                            |   |
| 14   | 0.006                                   | 0.046                         | 0.006                              | 0.021                         | 0.131                            |   |
| 15   | 0.022                                   | 0.054                         | 0.018                              | 0.067                         | 0.150                            |   |
| 16   | 0.006                                   | 0.043                         | 0.006                              | 0.021                         | 0.115                            |   |
| 17   | 0.020                                   | 0.048                         | 0.028                              | 0.101                         | 0.132                            |   |
| 18   | 0.006                                   | 0.046                         | 0.005                              | 0.019                         | 0.102                            |   |
| 19   | 0.005                                   | 0.035                         | 0.037                              | 0.027                         | 0.118                            |   |
| 20   | 0.005                                   | 0.040                         | 0.005                              | 0.020                         | 0.092                            |   |
| 21   | 0.009                                   | 0.068                         | 0.007                              | 0.027                         | 0.107                            | 0.160                                       |
| 22   | 0.007                                   | 0.049                         | 0.006                              | 0.023                         | 0.084                            |   |
| 23   | 0.025                                   | 0.038                         | 0.028                              | 0.021                         | 0.098                            | 0.147                                       |
| 24   | 0.005                                   | 0.040                         | 0.005                              | 0.020                         | 0.077                            |   |
| 25   | 0.045                                   | 0.034                         | 0.027                              | 0.020                         | 0.090                            | 0.135                                       |
| 26   | 0.007                                   | 0.053                         | 0.006                              | 0.022                         | 0.071                            |   |
| 27   | 0.005                                   | 0.037                         | 0.005                              | 0.020                         | 0.083                            | 0.124                                       |
| 28   | 0.005                                   | 0.035                         | 0.007                              | 0.027                         | 0.066                            |   |
| 29   | 0.021                                   | 0.030                         | 0.019                              | 0.068                         | 0.078                            | 0.117                                       |
| 30   | 0.004                                   | 0.031                         | 0.006                              | 0.021                         | 0.061                            |   |

# Annex to 6136782.03AOC

|    |       |       |       |       |       |       |
|----|-------|-------|-------|-------|-------|-------|
| 31 | 0.011 | 0.029 | 0.028 | 0.021 | 0.073 | 0.109 |
| 32 | 0.005 | 0.036 | 0.006 | 0.020 | 0.058 |       |
| 33 | 0.005 | 0.040 | 0.005 | 0.018 | 0.068 | 0.102 |
| 34 | 0.007 | 0.052 | 0.008 | 0.028 | 0.054 |       |
| 35 | 0.009 | 0.035 | 0.014 | 0.053 | 0.064 | 0.096 |
| 36 | 0.005 | 0.038 | 0.006 | 0.021 | 0.051 |       |
| 37 | 0.021 | 0.040 | 0.019 | 0.037 | 0.061 | 0.091 |
| 38 | 0.006 | 0.040 | 0.010 | 0.036 | 0.048 |       |
| 39 | 0.004 | 0.031 | 0.005 | 0.018 | 0.058 | 0.087 |
| 40 | 0.005 | 0.036 | 0.005 | 0.019 | 0.046 |       |

Note the higher limits for odd harmonics 21 and above are only allowable under certain conditions, if these higher limits are utilised please state the exemption used as detailed in part 6.2.3.4 of BS EN 61000-3-2 in the box below.

| Model: BNT010KTL   |   |                               |                                    |                               |                                  |   |
|--|---|-------------------------------|------------------------------------|-------------------------------|----------------------------------|---|
| L1   |   |                               |                                    |                               |                                  |   |
| Micro-generator tested to BS EN 61000-3-2  |   |                               |                                    |                               |                                  |   |
| Micro-generator rating per phase (rpp)   |   |                               |                                    | 3.33                          | kW                               |   |
| For 3-phase <b>Micro-generators</b> , tick this box if harmonic measurements are identical for all three phases. If the harmonics are not identical for each phase, please replicate this section with the results for each phase. |   |                               |                                    | three phase PV inverter       |                                  |   |
| Harmonic   | At 45-55% of <b>Registered Capacity</b> |                               | 100% of <b>Registered Capacity</b> |                               |                                  |   |
|  | Measured Value MV in Amps               | Normalised Value (NV) in Amps | Measured Value MV in Amps          | Normalised Value (NV) in Amps | Limit in BS EN 61000-3-2 in Amps | Higher limit for odd harmonics 21 and above |
| 2  | 0.045                                   | 0.099                         | 0.096                              | 0.106                         | 1.080                            |   |
| 3  | 0.036                                   | 0.079                         | 0.024                              | 0.026                         | 2.300                            |   |
| 4  | 0.013                                   | 0.029                         | 0.013                              | 0.014                         | 0.430                            |   |
| 5  | 0.096                                   | 0.212                         | 0.091                              | 0.100                         | 1.140                            |   |
| 6  | 0.008                                   | 0.018                         | 0.009                              | 0.010                         | 0.300                            |   |
| 7  | 0.073                                   | 0.161                         | 0.059                              | 0.065                         | 0.770                            |   |
| 8  | 0.007                                   | 0.015                         | 0.007                              | 0.008                         | 0.230                            |   |
| 9  | 0.019                                   | 0.042                         | 0.014                              | 0.015                         | 0.400                            |   |
| 10   | 0.007                                   | 0.015                         | 0.006                              | 0.007                         | 0.184                            |   |
| 11   | 0.091                                   | 0.201                         | 0.078                              | 0.086                         | 0.330                            |   |
| 12   | 0.005                                   | 0.011                         | 0.005                              | 0.006                         | 0.153                            |   |
| 13   | 0.070                                   | 0.155                         | 0.075                              | 0.083                         | 0.210                            |   |
| 14   | 0.006                                   | 0.013                         | 0.004                              | 0.004                         | 0.131                            |   |
| 15   | 0.015                                   | 0.033                         | 0.010                              | 0.011                         | 0.150                            |   |
| 16   | 0.007                                   | 0.015                         | 0.006                              | 0.007                         | 0.115                            |   |
| 17   | 0.047                                   | 0.104                         | 0.053                              | 0.059                         | 0.132                            |   |



# Annex to 6136782.03AOC

|    |       |       |       |       |       |       |
|----|-------|-------|-------|-------|-------|-------|
| 18 | 0.004 | 0.009 | 0.005 | 0.006 | 0.102 |       |
| 19 | 0.040 | 0.088 | 0.056 | 0.062 | 0.118 |       |
| 20 | 0.005 | 0.011 | 0.006 | 0.007 | 0.092 |       |
| 21 | 0.009 | 0.020 | 0.008 | 0.009 | 0.107 | 0.160 |
| 22 | 0.005 | 0.011 | 0.004 | 0.004 | 0.084 |       |
| 23 | 0.018 | 0.040 | 0.026 | 0.029 | 0.098 | 0.147 |
| 24 | 0.005 | 0.011 | 0.004 | 0.004 | 0.077 |       |
| 25 | 0.012 | 0.026 | 0.041 | 0.045 | 0.090 | 0.135 |
| 26 | 0.004 | 0.009 | 0.007 | 0.008 | 0.071 |       |
| 27 | 0.004 | 0.009 | 0.010 | 0.011 | 0.083 | 0.124 |
| 28 | 0.004 | 0.009 | 0.004 | 0.004 | 0.066 |       |
| 29 | 0.014 | 0.031 | 0.016 | 0.018 | 0.078 | 0.117 |
| 30 | 0.007 | 0.015 | 0.005 | 0.006 | 0.061 |       |
| 31 | 0.015 | 0.033 | 0.027 | 0.030 | 0.073 | 0.109 |
| 32 | 0.004 | 0.009 | 0.007 | 0.008 | 0.058 |       |
| 33 | 0.006 | 0.013 | 0.012 | 0.013 | 0.068 | 0.102 |
| 34 | 0.004 | 0.009 | 0.006 | 0.007 | 0.054 |       |
| 35 | 0.009 | 0.020 | 0.020 | 0.022 | 0.064 | 0.096 |
| 36 | 0.004 | 0.009 | 0.006 | 0.007 | 0.051 |       |
| 37 | 0.017 | 0.038 | 0.020 | 0.022 | 0.061 | 0.091 |
| 38 | 0.004 | 0.009 | 0.006 | 0.007 | 0.048 |       |
| 39 | 0.006 | 0.013 | 0.013 | 0.014 | 0.058 | 0.087 |
| 40 | 0.003 | 0.007 | 0.006 | 0.007 | 0.046 |       |

Note the higher limits for odd harmonics 21 and above are only allowable under certain conditions, if these higher limits are utilised please state the exemption used as detailed in part 6.2.3.4 of BS EN 61000-3-2 in the box below.

**Annex to 6136782.03AOC**

| Model: BNT010KTL   |   |                               |                                    |                               |                                  |   |
|--|---|-------------------------------|------------------------------------|-------------------------------|----------------------------------|---|
| L2   |   |                               |                                    |                               |                                  |   |
| <b>Micro-generator</b> tested to BS EN 61000-3-2   |   |                               |                                    |                               |                                  |   |
| <b>Micro-generator</b> rating per phase (rpp)  |   |                               |                                    | 3.33                          | kW                               |   |
| For 3-phase <b>Micro-generators</b> , tick this box if harmonic measurements are identical for all three phases. If the harmonics are not identical for each phase, please replicate this section with the results for each phase. |   |                               |                                    | three phase PV inverter       |                                  |   |
| Harmonic   | At 45-55% of <b>Registered Capacity</b> |                               | 100% of <b>Registered Capacity</b> |                               |                                  |   |
|  | Measured Value MV in Amps               | Normalised Value (NV) in Amps | Measured Value MV in Amps          | Normalised Value (NV) in Amps | Limit in BS EN 61000-3-2 in Amps | Higher limit for odd harmonics 21 and above |
| 2  | 0.036                                   | 0.079                         | 0.091                              | 0.100                         | 1.080                            |   |
| 3  | 0.068                                   | 0.150                         | 0.028                              | 0.031                         | 2.300                            |   |
| 4  | 0.011                                   | 0.024                         | 0.013                              | 0.014                         | 0.430                            |   |
| 5  | 0.123                                   | 0.272                         | 0.126                              | 0.139                         | 1.140                            |   |
| 6  | 0.009                                   | 0.020                         | 0.029                              | 0.032                         | 0.300                            |   |
| 7  | 0.111                                   | 0.245                         | 0.112                              | 0.124                         | 0.770                            |   |
| 8  | 0.007                                   | 0.015                         | 0.008                              | 0.009                         | 0.230                            |   |
| 9  | 0.021                                   | 0.046                         | 0.008                              | 0.009                         | 0.400                            |   |
| 10   | 0.007                                   | 0.015                         | 0.008                              | 0.009                         | 0.184                            |   |
| 11   | 0.096                                   | 0.212                         | 0.085                              | 0.094                         | 0.330                            |   |
| 12   | 0.009                                   | 0.020                         | 0.016                              | 0.018                         | 0.153                            |   |
| 13   | 0.075                                   | 0.166                         | 0.067                              | 0.074                         | 0.210                            |   |
| 14   | 0.006                                   | 0.013                         | 0.006                              | 0.007                         | 0.131                            |   |
| 15   | 0.014                                   | 0.031                         | 0.013                              | 0.014                         | 0.150                            |   |
| 16   | 0.007                                   | 0.015                         | 0.006                              | 0.007                         | 0.115                            |   |
| 17   | 0.052                                   | 0.115                         | 0.055                              | 0.061                         | 0.132                            |   |
| 18   | 0.007                                   | 0.015                         | 0.010                              | 0.011                         | 0.102                            |   |
| 19   | 0.040                                   | 0.088                         | 0.059                              | 0.065                         | 0.118                            |   |
| 20   | 0.005                                   | 0.011                         | 0.008                              | 0.009                         | 0.092                            |   |
| 21   | 0.006                                   | 0.013                         | 0.011                              | 0.012                         | 0.107                            | 0.160                                       |
| 22   | 0.006                                   | 0.013                         | 0.005                              | 0.006                         | 0.084                            |   |
| 23   | 0.024                                   | 0.053                         | 0.026                              | 0.029                         | 0.098                            | 0.147                                       |
| 24   | 0.005                                   | 0.011                         | 0.006                              | 0.007                         | 0.077                            |   |
| 25   | 0.019                                   | 0.042                         | 0.041                              | 0.045                         | 0.090                            | 0.135                                       |
| 26   | 0.006                                   | 0.013                         | 0.012                              | 0.013                         | 0.071                            |   |

# Annex to 6136782.03AOC

|    |       |       |       |       |       |       |
|----|-------|-------|-------|-------|-------|-------|
| 27 | 0.005 | 0.011 | 0.009 | 0.010 | 0.083 | 0.124 |
| 28 | 0.004 | 0.009 | 0.005 | 0.006 | 0.066 |       |
| 29 | 0.012 | 0.026 | 0.018 | 0.020 | 0.078 | 0.117 |
| 30 | 0.006 | 0.013 | 0.006 | 0.007 | 0.061 |       |
| 31 | 0.012 | 0.026 | 0.028 | 0.031 | 0.073 | 0.109 |
| 32 | 0.005 | 0.011 | 0.009 | 0.010 | 0.058 |       |
| 33 | 0.005 | 0.011 | 0.008 | 0.009 | 0.068 | 0.102 |
| 34 | 0.006 | 0.013 | 0.008 | 0.009 | 0.054 |       |
| 35 | 0.014 | 0.031 | 0.018 | 0.020 | 0.064 | 0.096 |
| 36 | 0.005 | 0.011 | 0.006 | 0.007 | 0.051 |       |
| 37 | 0.010 | 0.022 | 0.021 | 0.023 | 0.061 | 0.091 |
| 38 | 0.006 | 0.013 | 0.007 | 0.008 | 0.048 |       |
| 39 | 0.006 | 0.013 | 0.010 | 0.011 | 0.058 | 0.087 |
| 40 | 0.005 | 0.011 | 0.006 | 0.007 | 0.046 |       |

Note the higher limits for odd harmonics 21 and above are only allowable under certain conditions, if these higher limits are utilised please state the exemption used as detailed in part 6.2.3.4 of BS EN 61000-3-2 in the box below.

| Model: BNT010KTL   |   |                               |                                    |                               |                                  |   |
|--|---|-------------------------------|------------------------------------|-------------------------------|----------------------------------|---|
| L3   |   |                               |                                    |                               |                                  |   |
| <b>Micro-generator</b> tested to BS EN 61000-3-2   |   |                               |                                    |                               |                                  |   |
| <b>Micro-generator</b> rating per phase (rpp)  |   |                               |                                    | 3.33                          | kW                               |   |
| For 3-phase <b>Micro-generators</b> , tick this box if harmonic measurements are identical for all three phases. If the harmonics are not identical for each phase, please replicate this section with the results for each phase. |   |                               |                                    | three phase PV inverter       |                                  |   |
| Harmonic   | At 45-55% of <b>Registered Capacity</b> |                               | 100% of <b>Registered Capacity</b> |                               |                                  |   |
|  | Measured Value MV in Amps               | Normalised Value (NV) in Amps | Measured Value MV in Amps          | Normalised Value (NV) in Amps | Limit in BS EN 61000-3-2 in Amps | Higher limit for odd harmonics 21 and above |
| 2  | 0.051                                   | 0.113                         | 0.056                              | 0.062                         | 1.080                            |   |
| 3  | 0.052                                   | 0.115                         | 0.034                              | 0.038                         | 2.300                            |   |
| 4  | 0.011                                   | 0.024                         | 0.010                              | 0.011                         | 0.430                            |   |
| 5  | 0.082                                   | 0.181                         | 0.091                              | 0.100                         | 1.140                            |   |
| 6  | 0.008                                   | 0.018                         | 0.025                              | 0.028                         | 0.300                            |   |
| 7  | 0.058                                   | 0.128                         | 0.064                              | 0.071                         | 0.770                            |   |
| 8  | 0.008                                   | 0.018                         | 0.007                              | 0.008                         | 0.230                            |   |
| 9  | 0.012                                   | 0.026                         | 0.011                              | 0.012                         | 0.400                            |   |
| 10   | 0.007                                   | 0.015                         | 0.006                              | 0.007                         | 0.184                            |   |
| 11   | 0.073                                   | 0.161                         | 0.071                              | 0.078                         | 0.330                            |   |
| 12   | 0.008                                   | 0.018                         | 0.014                              | 0.015                         | 0.153                            |   |

# Annex to 6136782.03AOC

|    |       |       |       |       |       |       |
|----|-------|-------|-------|-------|-------|-------|
| 13 | 0.077 | 0.170 | 0.060 | 0.066 | 0.210 |       |
| 14 | 0.005 | 0.011 | 0.007 | 0.008 | 0.131 |       |
| 15 | 0.020 | 0.044 | 0.018 | 0.020 | 0.150 |       |
| 16 | 0.009 | 0.020 | 0.007 | 0.008 | 0.115 |       |
| 17 | 0.032 | 0.071 | 0.051 | 0.056 | 0.132 |       |
| 18 | 0.005 | 0.011 | 0.007 | 0.008 | 0.102 |       |
| 19 | 0.051 | 0.113 | 0.056 | 0.062 | 0.118 |       |
| 20 | 0.004 | 0.009 | 0.005 | 0.006 | 0.092 |       |
| 21 | 0.008 | 0.018 | 0.009 | 0.010 | 0.107 | 0.160 |
| 22 | 0.004 | 0.009 | 0.005 | 0.006 | 0.084 |       |
| 23 | 0.019 | 0.042 | 0.017 | 0.019 | 0.098 | 0.147 |
| 24 | 0.005 | 0.011 | 0.008 | 0.009 | 0.077 |       |
| 25 | 0.018 | 0.040 | 0.037 | 0.041 | 0.090 | 0.135 |
| 26 | 0.006 | 0.013 | 0.005 | 0.006 | 0.071 |       |
| 27 | 0.004 | 0.009 | 0.009 | 0.010 | 0.083 | 0.124 |
| 28 | 0.004 | 0.009 | 0.006 | 0.007 | 0.066 |       |
| 29 | 0.009 | 0.020 | 0.011 | 0.012 | 0.078 | 0.117 |
| 30 | 0.005 | 0.011 | 0.008 | 0.009 | 0.061 |       |
| 31 | 0.012 | 0.026 | 0.035 | 0.039 | 0.073 | 0.109 |
| 32 | 0.004 | 0.009 | 0.004 | 0.004 | 0.058 |       |
| 33 | 0.005 | 0.011 | 0.008 | 0.009 | 0.068 | 0.102 |
| 34 | 0.008 | 0.018 | 0.007 | 0.008 | 0.054 |       |
| 35 | 0.010 | 0.022 | 0.019 | 0.021 | 0.064 | 0.096 |
| 36 | 0.006 | 0.013 | 0.006 | 0.007 | 0.051 |       |
| 37 | 0.016 | 0.035 | 0.026 | 0.029 | 0.061 | 0.091 |
| 38 | 0.007 | 0.015 | 0.007 | 0.008 | 0.048 |       |
| 39 | 0.005 | 0.011 | 0.006 | 0.007 | 0.058 | 0.087 |
| 40 | 0.005 | 0.011 | 0.006 | 0.007 | 0.046 |       |

Note the higher limits for odd harmonics 21 and above are only allowable under certain conditions, if these higher limits are utilised please state the exemption used as detailed in part 6.2.3.4 of BS EN 61000-3-2 in the box below.

| 3. Power Quality – Voltage fluctuations and Flicker:   |   |                 |          |               |                  |          |                 | P                          |
|--|---|-----------------|----------|---------------|------------------|----------|-----------------|----------------------------|
| <p>These tests should be undertaken in accordance with EREC G98 Annex A1 A.1.3.3 (<b>Inverter</b> connected) or Annex A2 A.2.3.3 (Synchronous).</p> <p>The standard test impedance is 0.4 <math>\Omega</math> for a single phase <b>Micro-generating Plant</b> (and for a two phase unit in a three phase system) and 0.24 <math>\Omega</math> for a three phase <b>Micro-generating Plant</b> (and for a two phase unit in a split phase system). Please ensure that both test and standard impedance are completed on this form. If the test impedance (or the measured impedance) is different to the standard impedance, it must be normalised to the standard impedance as follows (where the <b>Power Factor</b> of the generation output is 0.98 or above):</p> <p>d max normalised value = (Standard impedance / Measured impedance) x Measured value.</p> <p>Where the <b>Power Factor</b> of the output is under 0.98 then the X to R ratio of the test impedance should be close to that of the standard impedance.</p> <p>The stopping test should be a trip from full load operation.</p> <p>The duration of these tests needs to comply with the particular requirements set out in the testing notes for the technology under test.</p> <p>The test date and location must be declared.</p> |   |                 |          |               |                  |          |                 |                            |
| Test start date  | 2022-07-06  |                 |          | Test end date | 2022-07-06       |          |                 |                            |
| Test location  | No.99, Hongye Road, Suzhou Industrial Park, Suzhou, Jiangsu, P.R. China |                 |          |               |                  |          |                 |                            |
| Model:   | BNT010KTL   |                 |          |               |                  |          |                 |                            |
| L1   |   |                 |          |               |                  |          |                 |                            |
|  | Starting  |                 |          | Stopping      |                  |          | Running         |                            |
|  | d(max)  | d(c)            | d(t)     | d(max)        | d(c)             | d(t)     | P <sub>st</sub> | P <sub>lt</sub><br>2 hours |
| Measured Values at test impedance  | 0.20  | 0.04            | 0        | 0.20          | 0.05             | 0        | 0.14            | 0.11                       |
| Normalised to standard impedance   | 0.20  | 0.04            | 0        | 0.20          | 0.05             | 0        | 0.14            | 0.11                       |
| Normalised to required maximum impedance   | N/A   | N/A             | N/A      | N/A           | N/A              | N/A      | N/A             | N/A                        |
| Limits set under BS EN 61000-3-11  | 4%  | 3.3%            | 3.3%     | 4%            | 3.3%             | 3.3%     | 1.0             | 0.65                       |
|  |   |                 |          |               |                  |          |                 |                            |
| Test Impedance   | R   | 0.24            | $\Omega$ | XI            | 0.15             | $\Omega$ |                 |                            |
| Standard Impedance   | R   | 0.24 *<br>0.4 ^ | $\Omega$ | XI            | 0.15 *<br>0.25 ^ | $\Omega$ |                 |                            |
| Maximum Impedance  | R   | N/A #           | $\Omega$ | XI            | N/A #            | $\Omega$ |                 |                            |
| <p>*Applies to three phase and split single phase <b>Micro-generators</b>. Delete as appropriate.</p> <p>^ Applies to single phase <b>Micro-generators</b> and <b>Micro-generators</b> using two phases on a three phase system. Delete as appropriate.</p>  |   |                 |          |               |                  |          |                 |                            |

|        |           |
|--------|-----------|
| Model: | BNT010KTL |
|--------|-----------|



| L2   |          |                 |      |          |                  |      |                 |                            |
|--|----------|-----------------|------|----------|------------------|------|-----------------|----------------------------|
|  | Starting |                 |      | Stopping |                  |      | Running         |                            |
|  | d(max)   | d(c)            | d(t) | d(max)   | d(c)             | d(t) | P <sub>st</sub> | P <sub>It</sub><br>2 hours |
| Measured Values at test impedance  | 0.26     | 0.06            | 0    | 0.28     | 0.06             | 0    | 0.12            | 0.10                       |
| Normalised to standard impedance   | 0.26     | 0.06            | 0    | 0.28     | 0.06             | 0    | 0.12            | 0.10                       |
| Normalised to required maximum impedance   | N/A      | N/A             | N/A  | N/A      | N/A              | N/A  | N/A             | N/A                        |
| Limits set under BS EN 61000-3-11  | 4%       | 3.3%            | 3.3% | 4%       | 3.3%             | 3.3% | 1.0             | 0.65                       |
|  |          |                 |      |          |                  |      |                 |                            |
| Test Impedance   | R        | 0.24            | Ω    | XI       | 0.15             | Ω    |                 |                            |
| Standard Impedance   | R        | 0.24 *<br>0.4 ^ | Ω    | XI       | 0.15 *<br>0.25 ^ | Ω    |                 |                            |
| Maximum Impedance  | R        | N/A #           | Ω    | XI       | N/A #            | Ω    |                 |                            |
| *Applies to three phase and split single phase <b>Micro-generators</b> . Delete as appropriate.  |          |                 |      |          |                  |      |                 |                            |
| ^ Applies to single phase <b>Micro-generators</b> and <b>Micro-generators</b> using two phases on a three phase system. Delete as appropriate. |          |                 |      |          |                  |      |                 |                            |

|  |           |      |      |          |      |      |                 |                            |
|--|-----------|------|------|----------|------|------|-----------------|----------------------------|
| Model:                                   | BNT010KTL |      |      |          |      |      |                 |                            |
| L3                                       |           |      |      |          |      |      |                 |                            |
|  | Starting  |      |      | Stopping |      |      | Running         |                            |
|  | d(max)    | d(c) | d(t) | d(max)   | d(c) | d(t) | P <sub>st</sub> | P <sub>lt</sub><br>2 hours |
| Measured Values at test impedance        | 0.26      | 0.06 | 0    | 0.28     | 0.06 | 0    | 0.12            | 0.10                       |
| Normalised to standard impedance         | 0.26      | 0.06 | 0    | 0.28     | 0.06 | 0    | 0.12            | 0.10                       |
| Normalised to required maximum impedance | N/A       | N/A  | N/A  | N/A      | N/A  | N/A  | N/A             | N/A                        |
| Limits set under BS EN 61000-3-11        | 4%        | 3.3% | 3.3% | 4%       | 3.3% | 3.3% | 1.0             | 0.65                       |
|  |           |      |      |          |      |      |                 |                            |
| Test Impedance                           | R         | 0.24 | Ω    | XI       |      | 0.15 | Ω               |                            |

## Annex to 6136782.03AOC

|                    |   |                 |   |    |                  |   |
|--------------------|---|-----------------|---|----|------------------|---|
| Standard Impedance | R | 0.24 *<br>0.4 ^ | Ω | XI | 0.15 *<br>0.25 ^ | Ω |
| Maximum Impedance  | R | N/A #           | Ω | XI | N/A #            | Ω |

\*Applies to three phase and split single phase **Micro-generators**. Delete as appropriate.  
^ Applies to single phase **Micro-generators** and **Micro-generators** using two phases on a three phase system. Delete as appropriate.

| 4. Power quality – DC injection:  |        |        |        |        | P |
|---|--------|--------|--------|--------|---|
| This test should be carried out in accordance with A 1.3.4 as applicable.<br>The % <b>DC</b> injection (“as % of rated AC current” below) is calculated as follows:<br>% <b>DC</b> injection = Recorded <b>DC</b> value in Amps / base current<br>where the base current is the <b>Registered Capacity</b> (W) / 230 V. The % <b>DC</b> injection should not be greater than 0.25%. |        |        |        |        |   |
| Model: BNT003KTL  |        |        |        |        |   |
| L1  |        |        |        |        |   |
| Test power level  | 20%    | 50%    | 75%    | 100%   |   |
| Recorded DC injection value in Amps   | -0.010 | -0.010 | -0.005 | -0.007 |   |
| as % of rated AC current  | -0.08% | -0.08% | -0.04% | -0.05% |   |
| Limit   | 0.25%  | 0.25%  | 0.25%  | 0.25%  |   |
| Model: BNT003KTL  |        |        |        |        |   |
| L2  |        |        |        |        |   |
| Test power level  | 20%    | 50%    | 75%    | 100%   |   |
| Recorded DC injection value in Amps   | -0.011 | -0.008 | -0.006 | -0.006 |   |
| as % of rated AC current  | -0.08% | -0.06% | -0.05% | -0.05% |   |
| Limit   | 0.25%  | 0.25%  | 0.25%  | 0.25%  |   |
| Model: BNT003KTL  |        |        |        |        |   |
| L3  |        |        |        |        |   |
| Test power level  | 20%    | 50%    | 75%    | 100%   |   |
| Recorded DC injection value in Amps   | -0.009 | -0.009 | -0.005 | -0.006 |   |
| as % of rated AC current  | -0.07% | -0.07% | -0.04% | -0.05% |   |
| Limit   | 0.25%  | 0.25%  | 0.25%  | 0.25%  |   |

|                                     |        |        |        |        |  |
|-------------------------------------|--------|--------|--------|--------|--|
| Model: BNT010KTL                    |        |        |        |        |  |
| L1                                  |        |        |        |        |  |
| Test power level                    | 20%    | 50%    | 75%    | 100%   |  |
| Recorded DC injection value in Amps | -0.027 | -0.028 | -0.028 | -0.026 |  |
| as % of rated AC current            | -0.06% | -0.06% | -0.06% | -0.06% |  |
| Limit                               | 0.25%  | 0.25%  | 0.25%  | 0.25%  |  |
| Model: BNT010KTL                    |        |        |        |        |  |

## Annex to 6136782.03AOC

| L2                                  |        |        |        |        |
|-------------------------------------|--------|--------|--------|--------|
| Test power level                    | 20%    | 50%    | 75%    | 100%   |
| Recorded DC injection value in Amps | -0.033 | -0.033 | -0.033 | -0.034 |
| as % of rated AC current            | -0.08% | -0.08% | -0.08% | -0.08% |
| Limit                               | 0.25%  | 0.25%  | 0.25%  | 0.25%  |
| Model: BNT010KTL                    |        |        |        |        |
| L3                                  |        |        |        |        |
| Test power level                    | 20%    | 50%    | 75%    | 100%   |
| Recorded DC injection value in Amps | -0.023 | -0.027 | -0.024 | -0.028 |
| as % of rated AC current            | -0.05% | -0.06% | -0.06% | -0.06% |
| Limit                               | 0.25%  | 0.25%  | 0.25%  | 0.25%  |

| 5. Power Factor:   |                   |              |                | P |
|--|-------------------|--------------|----------------|---|
| This test shall be carried out in accordance with A.1.3.2 and A.2.3.2 at three voltage levels and at <b>Registered Capacity</b> and the measured <b>Power Factor</b> must be greater than 0.95 to pass. Voltage to be maintained within $\pm 1.5\%$ of the stated level during the test. |                   |              |                |   |
| Model: BNT010KTL   |                   |              |                |   |
| Voltage  | 0.94 pu (216.2 V) | 1 pu (230 V) | 1.1 pu (253 V) |   |
| Measured value   | 0.9999            | 0.9999       | 0.9999         |   |
| <b>Power Factor</b> Limit  | >0.95             | >0.95        | >0.95          |   |
| Model: BNT003KTL   |                   |              |                |   |
| Voltage  | 0.94 pu (216.2 V) | 1 pu (230 V) | 1.1 pu (253 V) |   |
| Measured value   | 0.9990            | 0.9990       | 0.9990         |   |
| <b>Power Factor</b> Limit  | >0.95             | >0.95        | >0.95          |   |

| 6. Protection – Frequency tests:   |           |            |           |            |                    | P               |
|--|-----------|------------|-----------|------------|--------------------|-----------------|
| These tests should be carried out in accordance with Annex A1 A.1.2.3 ( <b>Inverter</b> connected) or Annex A2 A.2.2.3 (Synchronous). For trip tests, frequency and time delay should be stated. For “no trip tests”, “no trip” can be stated. |           |            |           |            |                    |                 |
| Model: BNT010KTL   |           |            |           |            |                    |                 |
| Function   | Setting   |            | Trip test |            | “No trip tests”    |                 |
|  | Frequency | Time delay | Frequency | Time delay | Frequency / time   | Confirm no trip |
| U/F stage 1  | 47.5 Hz   | 20 s       | 47.5      | 20.03s     | 47.7 Hz<br>30 s    | No trip         |
| U/F stage 2  | 47.0 Hz   | 0.5 s      | 46.99     | 0.562s     | 47.2 Hz<br>19.5 s  | No trip         |
|  |           |            |           |            | 46.8 Hz<br>0.45 s  | No trip         |
| O/F  | 52.0 Hz   | 0.5 s      | 52.01     | 0.557s     | 51.8 Hz<br>120.0 s | No trip         |

## Annex to 6136782.03AOC

|  |  |  |  |  |                   |         |
|--|--|--|--|--|-------------------|---------|
|  |  |  |  |  | 52.2 Hz<br>0.45 s | No trip |
| <p>Note: For frequency trip tests the frequency required to trip is the setting <math>\pm 0.1</math> Hz. In order to measure the time delay a larger deviation than the minimum required to operate the projection can be used. The “No trip tests” need to be carried out at the setting <math>\pm 0.2</math> Hz and for the relevant times as shown in the table above to ensure that the protection will not trip in error.</p> |  |  |  |  |                   |         |

| 7. Protection – Voltage tests:   |                      |            |           |            |                   | P               |
|--|----------------------|------------|-----------|------------|-------------------|-----------------|
| <p>These tests should be carried out in accordance with Annex A1 A.1.2.2 (<b>Inverter</b> connected) or Annex A2 A.2.2.2 (Synchronous). For trip tests, voltage and time delay should be stated. For “no trip tests”, “no trip” can be stated.</p> |                      |            |           |            |                   |                 |
| Model: BNT010KTL   |                      |            |           |            |                   |                 |
| L1   |                      |            |           |            |                   |                 |
| Function   | Setting              |            | Trip test |            | “No trip tests”   |                 |
|  | Voltage              | Time delay | Voltage   | Time delay | Voltage / time    | Confirm no trip |
| U/V  | 0.8 pu<br>(184 V)    | 2.5 s      | 183.5     | 2.562      | 188 V<br>5.0 s    | No trip         |
|  |                      |            |           |            | 180 V<br>2.45 s   | No trip         |
| O/V stage 1  | 1.14 pu<br>(262.2 V) | 1.0 s      | 262.8     | 1.025      | 258.2 V<br>5.0 s  | No trip         |
| O/V stage 2  | 1.19 pu<br>(273.7 V) | 0.5 s      | 273.6     | 0.561      | 269.7 V<br>0.95 s | No trip         |
|  |                      |            |           |            | 277.7 V<br>0.45 s | No trip         |

| Model: BNT010KTL |                      |            |           |            |                   |                 |
|------------------|----------------------|------------|-----------|------------|-------------------|-----------------|
| L2               |                      |            |           |            |                   |                 |
| Function         | Setting              |            | Trip test |            | “No trip tests”   |                 |
|                  | Voltage              | Time delay | Voltage   | Time delay | Voltage / time    | Confirm no trip |
| U/V              | 0.8 pu<br>(184 V)    | 2.5 s      | 183.6     | 2.552      | 188 V<br>5.0 s    | No trip         |
|                  |                      |            |           |            | 180 V<br>2.45 s   | No trip         |
| O/V stage 1      | 1.14 pu<br>(262.2 V) | 1.0 s      | 263.1     | 1.042      | 258.2 V<br>5.0 s  | No trip         |
| O/V stage 2      | 1.19 pu<br>(273.7 V) | 0.5 s      | 274.3     | 0.534      | 269.7 V<br>0.95 s | No trip         |
|                  |                      |            |           |            | 277.7 V<br>0.45 s | No trip         |

| Model: BNT010KTL |         |            |           |            |                 |                 |
|------------------|---------|------------|-----------|------------|-----------------|-----------------|
| L3               |         |            |           |            |                 |                 |
| Function         | Setting |            | Trip test |            | “No trip tests” |                 |
|                  | Voltage | Time delay | Voltage   | Time delay | Voltage / time  | Confirm no trip |
| U/V              | 0.8 pu  | 2.5 s      | 182.4     | 2.545      | 188 V           | No trip         |

## Annex to 6136782.03AOC

|             |                      |       |       |       |                   |         |
|-------------|----------------------|-------|-------|-------|-------------------|---------|
|             | (184 V)              |       |       |       | 5.0 s             |         |
|             |                      |       |       |       | 180 V<br>2.45 s   | No trip |
| O/V stage 1 | 1.14 pu<br>(262.2 V) | 1.0 s | 263.8 | 1.038 | 258.2 V<br>5.0 s  | No trip |
| O/V stage 2 | 1.19 pu<br>(273.7 V) | 0.5 s | 275.0 | 0.546 | 269.7 V<br>0.95 s | No trip |
|             |                      |       |       |       | 277.7 V<br>0.45 s | No trip |

Note: For Voltage tests the Voltage required to trip is the setting  $\pm 3.45$  V. The time delay can be measured at a larger deviation than the minimum required to operate the protection. The No trip tests need to be carried out at the setting  $\pm 4$  V and for the relevant times as shown in the table above to ensure that the protection will not trip in error.

| 8. Protection – Loss of Mains test:  |                         |                         |                         |                         |                         | P                        |
|--|-------------------------|-------------------------|-------------------------|-------------------------|-------------------------|--------------------------|
| For PV <b>Inverters</b> shall be tested in accordance with BS EN 62116. Other <b>Micro-generators</b> should be tested in accordance with A.2.2.4 at 10%, 55% and 100% of rated power.<br>For test condition A, EUT output = 100 % $P_n$ , test condition B, EUT output = 50 % to 66 % $P_n$ , and test condition C, EUT output = 25 % to 33 % $P_n$ . |                         |                         |                         |                         |                         |                          |
| Model: BNT010KTL   |                         |                         |                         |                         |                         |                          |
| For <b>Inverters</b> tested to BS EN 62116 the following sub set of tests should be recorded in the following table.   |                         |                         |                         |                         |                         |                          |
| Test Power and imbalance   | 33%<br>-5% Q<br>Test 22 | 66%<br>-5% Q<br>Test 12 | 100%<br>-5% P<br>Test 5 | 33%<br>+5% Q<br>Test 31 | 66%<br>+5% Q<br>Test 21 | 100%<br>+5% P<br>Test 10 |
| Trip time.<br><b>Limit is 0.5s</b>   | 0.171s                  | 0.176s                  | 0.184s                  | 0.174s                  | 0.176s                  | 0.178s                   |

| 8. Protection – Frequency change, Vector Shift Stability test:   |                 |             |                 | P |
|--|-----------------|-------------|-----------------|---|
| This test should be carried out in accordance with EREC G98 Annex A1 A.1.2.6 ( <b>Inverter</b> connected) or Annex A2 A.2.2.6 (Synchronous). Confirmation is required that the <b>Micro-generating Plant</b> does not trip under positive / negative vector shift. |                 |             |                 |   |
| Model: BNT010KTL   |                 |             |                 |   |
|  | Start Frequency | Change      | Confirm no trip |   |
| Positive Vector Shift  | 49.0 Hz         | +50 degrees | No trip         |   |
| Negative Vector Shift  | 50.0 Hz         | -50 degrees | No trip         |   |

| 8. Protection – Frequency change, RoCoF Stability test:   |                         |               |                 | P |
|---|-------------------------|---------------|-----------------|---|
| The requirement is specified in section 11.3, test procedure in Annex A.1.2.6 ( <b>Inverter</b> connected) or Annex A2 A.2.2.6 (Synchronous). Confirmation is required that the <b>Micro-generating Plant</b> does not trip for the duration of the ramp up and ramp down test. |                         |               |                 |   |
| Model: BNT010KTL  |                         |               |                 |   |
| Ramp range  | Test frequency ramp:    | Test Duration | Confirm no trip |   |
| 49.0 Hz to 51.0 Hz  | +0.95 Hzs <sup>-1</sup> | 2.1 s         | No trip         |   |
| 51.0 Hz to 49.0 Hz  | -0.95 Hzs <sup>-1</sup> | 2.1 s         | No trip         |   |



| 9. Limited Frequency Sensitive Mode – Over frequency test:  |   |                   |                         |                                    | P                               |
|---|---|-------------------|-------------------------|------------------------------------|---------------------------------|
| This test should be carried out in accordance with A.1.2.9. The test should be carried out using the specific threshold frequency of 50.4 Hz and <b>Droop</b> of 10%. The measurement tolerances are contained in A.1.2.9.  |   |                   |                         |                                    |                                 |
| Model: BNT010KTL  |   |                   |                         |                                    |                                 |
| Alternatively, simulation results should be noted below:  |   |                   |                         |                                    |                                 |
| Test sequence at<br><b>Registered Capacity &gt;80%</b>  | Measured<br><b>Active Power</b><br>Output (W) | Frequency<br>(Hz) | Calculated<br>droop (%) | Primary<br>Power<br>Source         | <b>Active Power</b><br>Gradient |
| Step a) 50.00 Hz ±0.01 Hz   | 10000.61                                      | 50.00             | -                       | Photovoltaic<br>array<br>simulator | -                               |
| Step b) 50.45 Hz ±0.05 Hz   | 9895.17                                       | 50.45             | 9.49                    |                                    | -                               |
| Step c) 50.70 Hz ±0.10 Hz   | 9357.79                                       | 50.70             | 9.34                    |                                    | -                               |
| Step d) 51.15 Hz ±0.05 Hz   | 8434.82                                       | 51.15             | 9.58                    |                                    | -                               |
| Step e) 50.70 Hz ±0.10 Hz   | 9369.30                                       | 50.70             | 9.50                    |                                    | -                               |
| Step f) 50.45 Hz ±0.05 Hz   | 9895.53                                       | 50.45             | 9.53                    |                                    | -                               |
| Step g) 50.00 Hz ±0.01 Hz   | 10000.36                                      | 50.00             | -                       |                                    | -                               |
| Test sequence at<br><b>Registered Capacity 40-60%</b>   | Measured<br><b>Active Power</b><br>Output (W) | Frequency<br>(Hz) | Calculated<br>droop (%) | Primary<br>Power<br>Source         | <b>Active Power</b><br>Gradient |
| Step a) 50.00 Hz ±0.01 Hz   | 5001.77                                       | 50.00             | -                       | Photovoltaic<br>array<br>simulator | -                               |
| Step b) 50.45 Hz ±0.05 Hz   | 4899.31                                       | 50.45             | 9.73                    |                                    | -                               |
| Step c) 50.70 Hz ±0.10 Hz   | 4367.48                                       | 50.70             | 9.46                    |                                    | -                               |
| Step d) 51.15 Hz ±0.05 Hz   | 3420.22                                       | 51.15             | 9.48                    |                                    | -                               |
| Step e) 50.70 Hz ±0.10 Hz   | 4365.84                                       | 50.70             | 9.43                    |                                    | -                               |
| Step f) 50.45 Hz ±0.05 Hz   | 4894.91                                       | 50.45             | 9.30                    |                                    | -                               |
| Step g) 50.00 Hz ±0.01 Hz   | 5001.07                                       | 50.00             | -                       |                                    | -                               |
| The frequency at each step should be maintained for at least one minute and the Active Power reduction in the form of a gradient determined and assessed for compliance with paragraph 11.2.3. The Droop should be determined from the measurements between 50.4 Hz and 51.15 Hz. The allowed tolerance for the frequency measurement shall be ± 0.05 Hz. The allowed tolerance for Active Power output measurement shall be ±10% of the required change in Active Power. |   |                   |                         |                                    |                                 |
| The resulting overall tolerance range for a nominal 10% Droop is +2.8% and – 1.5%, ie a Droop less than 12.8% and greater than 8.5%.  |   |                   |                         |                                    |                                 |

| 10. Power output with falling frequency test (For PV Inverter):   |   |                |                              | P |
|---|---|----------------|------------------------------|---|
| This test should be carried out in accordance with A.1.2.7.   |   |                |                              |   |
| Model: BNT010KTL  |   |                |                              |   |
| Test sequence   | Measured <b>Active Power</b> Output (W) | Frequency (Hz) | Primary power source         |   |
| Test a) 50 Hz ± 0.01 Hz   | 10030.59                                | 50.00          | Photovoltaic array simulator |   |
| Test b) Point between 49.5 Hz and 49.6 Hz   | 10029.18                                | 49.55          | Photovoltaic array simulator |   |
| Test c) Point between 47.5 Hz and 47.6 Hz   | 10026.53                                | 47.55          | Photovoltaic array simulator |   |
| <b>NOTE:</b><br>The operating point in Test (b) and (c) shall be maintained for at least 5 minutes  |   |                |                              |   |
| <b>The test is regarded as passed if:</b> <ul style="list-style-type: none"><li>• the Micro-generator does not disconnect from the network at the operating points a) to c) when the network frequency is changed and</li><li>• the Micro-generator does not reduce output energy at point b) and</li><li>• the power reduction at point c) is less than or equal to the allowed power reduction according to paragraph 9.4.2 (Figure 3).</li></ul> |   |                |                              |   |
| <b>The following data shall be documented:</b> <ul style="list-style-type: none"><li>• variation of the network frequency with time;</li><li>• the measured Active Power with time.</li></ul>   |   |                |                              |   |

| 12. Re-connection timer  |                |  |                           | P                         |
|--|----------------|--|---------------------------|---------------------------|
| Model: BNT010KTL   |                |  |                           |                           |
| Test should prove that the reconnection sequence starts after a minimum delay of 20 s for restoration of voltage and frequency to within the stage 1 settings of Table 2. Both the time delay setting and the measured delay should be provided in this form; both should be greater than 20 s to pass. Confirmation should be provided that the <b>Micro-generating Plant</b> does not reconnect at the voltage and frequency settings below; a statement of "no reconnection" can be made. |                |  |                           |                           |
| Time delay setting   | Measured delay | Checks on no reconnection when voltage or frequency is brought to just outside stage 1 limits of Table 10.1. |                           |                           |
| 60s  | 60.4s          | At 1.16 pu (266.2 V)   | At 0.78 pu (180.0 V)      | At 47.4 Hz                |
| Confirmation that the <b>Micro-generator</b> does not re-connect.  |                | No Reconnection  | No Reconnection           | No Reconnection           |
| Recover to normal operation range after confirmation of no connection  |                | Yes  | Yes                       | Yes                       |
| Confirmation that the Power Generating Module shall reconnect  |                | Reconnection after 61.0 s  | Reconnection after 61.1 s | Reconnection after 60.4 s |

| 13. Fault level contribution:  |          |       |                            |         | P          |
|--|----------|-------|----------------------------|---------|------------|
| These tests shall be carried out in accordance with EREC G98 Annex A1 A.1.3.5 ( <b>Inverter</b> connected) and Annex A2 A.2.3.4 (Synchronous). Please complete each entry, even if the fault contribution is zero.   |          |       |                            |         |            |
| Model: BNT010KTL   |          |       |                            |         |            |
| For machines with electro-magnetic output  |          |       | For <b>Inverter</b> output |         |            |
| Parameter  | Symbol   | Value | Time after fault           | Volts   | Amps       |
| Peak Short Circuit current   | $i_p$    | N/A   | 20ms                       | 17.41V  | 18.78A     |
| Initial Value of aperiodic current   | $A$      | N/A   | 100ms                      | 17.57V  | 16.72A     |
| Initial symmetrical short-circuit current*   | $I_k$    | N/A   | 250ms                      | 0       | 0          |
| Decaying (aperiodic) component of short circuit current*   | $i_{DC}$ | N/A   | 500ms                      | 0       | 0          |
| Reactance/Resistance Ratio of source*  | $X/R$    | N/A   | Time to trip               | 165.6ms | In seconds |
| For rotating machines and linear piston machines the test should produce a 0 s – 2 s plot of the short circuit current as seen at the <b>Micro-generator</b> terminals.<br>* Values for these parameters should be provided where the short circuit duration is sufficiently long to enable interpolation of the plot. |          |       |                            |         |            |

| 14. Logic interface (input port)  |  |
|---|--|
| Confirm that an input port is provided and can be used to reduce the <b>Active Power</b> output to zero   | Yes  |
| Provide high level description of logic interface, e.g. details in 9.4.3 such as AC or <b>DC</b> signal (the additional comments box below can be used)   | Yes  |
| 15. Self-Monitoring solid state switching: No specified test requirements.<br>Refer to EREC G98 Annex A1 A.1.3.6 (Inverter connected).  |  |
| It has been verified that in the event of the solid state switching device failing to disconnect the <b>Micro-generator</b> , the voltage on the output side of the switching device is reduced to a value below 50 V within 0.5 s.   | N/A  |
| 16. Cyber security  |  |
| Confirm that the <b>Manufacturer</b> or <b>Installer</b> of the <b>Micro-generator</b> has provided a statement describing how the <b>Micro-generator</b> has been designed to comply with cyber security requirements, as detailed in 9.7.   | Yes,<br>Manufacturer's declaration provided. |
| Additional comments.  |  |
| To short or open pin1 and pin5 of logic interface port (RS485 port) to control the inverter to normal or shutdown active power of output. A logic interface is provided that can be operated by an external switch or contactor. Users can install by themselves. Users install the switch connected to pin1 and pin5 of RS485 port and just need control the switch signal causing the switch to open or short. When the switch is closed, the inverter will operate normally. When the switch is opened, the inverter will cease to export active power within 5 seconds. The signal from the inverter that is being switched is DC (maximum value 3.3V). |  |